

The NEW Fischer Panda® 5.5e Inverter Generator, Designed for Your Boat

The Panda 5.5e is engineered to meet the modern boater's needs with its compact design, reliable performance, and advanced features. This generator ensures you can enjoy your time on the water without worrying about power constraints.

Elevate Your Boating Experience

Precision power for all your needs, from air conditioners to navigation systems. Its compact footprint is perfect for boats with limited space and height restrictions, integrating seamlessly into contemporary setups. Additionally, smart electronics provide quick troubleshooting through clear text messages.

Cruise with Confidence:

Panda 5.5e's innovative, compact design and advanced features provide everything you need to embrace the adventures that await you. If you are seeking the perfect balance of efficiency, performance and peace of mind, this is the generator you have been waiting for. For more information, give us a call.



Fischer Panda®



SMALL



LIGHT



QUIET

351 S. Andrews Ave., Pompano Beach, FL 33069

Call (800) 508-6494

Visit us at www.fischerpanda.com

or e-mail us at sales@fischerpanda.com



FEATURES INCLUDE:

- **Advanced Digital Control & Monitoring** • Graphic display with key data • Log data for preventative maintenance
- **Next-Level Integration & Remote Access** • NMEA 2000 compatibility for seamless MFD connection (Garmin, Raymarine, etc.) • Remote start and monitoring for convenience • Digital I/O for real-time generator status
- **Superior Engine Protection & Reliability** • Automatic preheating and fuel priming • Reduces cranking, preventing wear • Built-in control circuit for raw water valve to prevent damage (valve not included) • High starting capacity for heavy loads
- **Compact & Efficient Design** • Small footprint and low height for easier installation • Minimizes wet stacking, increasing longevity



Fischer Panda® 5.5e Inverter Specifications

Frequency (Hz)	60
Voltage (V)	120
Power Nominal (kW)	5.5
Current (A)	45.1
Engine Data	Kubota Z482
Cylinder/HP	2 cyl/13.3
Displacement	479 ccm/29.2 cu.in.
Cooling	Heat Exchanger
Noise Level (dBA @ 23 ft)	54
Length (inches)	21.3
Width (inches)	18.3
Height (inches)	21.9
Wet Weight Generator/Inverter (lbs)	223/14

Issued: 09/12/2025. Fischer Panda Generator is standard with a sound shield.

Remote Digital Panel



Inverter



OPTIONAL ACCESSORIES

External Soft Motor Mounts

External Soft Motor Mounts for extra smooth operation.



Vented Loop

(anti-siphon valve) Recommended for all installations. Prevents water from siphoning back to the engine and minimizes potential electrolysis. Made with a stainless-steel tube and nylon valve for long life and easy service.





Gas Separator

Exhaust water separator provides very low back pressure and extra quiet exhaust noise.



Low Profile Muffler

Low inlet muffler for installations where the muffler cannot be installed lower than the genset.



FischerPanda®

351 S. Andrews Ave., Pompano Beach, FL 33069

Call (800) 508-6494

Visit us at www.fischerpanda.com
or e-mail us at
sales@fischerpanda.com

